

Conventional Fire Alarm Control Panel *(2 Zone)*

HFP CP-2



Features

- ▶ Fully compliant with & tested to BS EN54-2 and BS EN54-4
- ▶ Compatible for use on BS5839: Part 1: 2002 installations
- ▶ 2-wire repeaters and ancillary boards
- ▶ Fully programmable using simple menu options
- ▶ Simple, installer friendly single board construction
- ▶ Compatible with Hochiki CDX range of devices
- ▶ Two monitored sounder outputs
- ▶ 3 Amp power supply
- ▶ Auxiliary power output

Description

The HFP CP range of conventional panels offers the same reliability, durability and flexibility already afforded by the HFP FIREline range of analogue control panels. 100% compatible with the complete Hochiki conventional range of products the HFP CP panels offer the installer complete flexibility and total peace of mind. Also available are a 4 zone (HFP CP-4), an 8 zone (HFP CP-8) and a range of Active Repeater panels (the HFP CP-R range).

Specification	
Enclosure	1.2mm Steel
Operating Temperature	-5°C to +50°C
Operating Humidity	< 95% (non condensing)
Cable Entries (20mm knockouts)	12 x top, 12 x top rear, 1 x left-hand side, 1 x right-hand side
Supply Voltage	230V AC (+10%/-15%)
Power Supply DC Rating	24V 3A
Battery Capacity	7Ah 12V (2 per panel)
Number of Fire Zones	2
Sounder Outputs	2 x 0.5A (max 1.6A over all outputs)
Contact Rating (Fault/Local Fire/Fire)	30V DC 1A
Detection Zone Current	1.6mA
Detection Zone End Of Line Resistor	6k8 5%
Sounder Output End Of Line Resistor	10k 5%
Weight	5.5Kg
Dimensions (mm)	385(W) x 310(H) x 92(D)